

CISCO - Instalowanie systemu operacyjnego

[illegible]

[illegible]

5343604 bytes copied in 15.930 secs (335443 bytes/sec)

— —

Przywracanie systemu operacyjnego z pliku/server tftpd:

— —

CTRL+Break - wchodzimy w ROMMON:

```
rommon 1 > IP ADDRESS=10.1.1.1
```

```
rommon 2 > IP SUBNET MASK=255.255.255.0
```

```
rommon 3 > TFTP SERVER=10.1.1.2
```

```
rommon 4 > TFTP FILE=c1700-y-mz.122-15.t5.bin
```

```
rommon 5 > tftpdnld
```

IP ADDRESS: 10.1.1.1

IP SUBNET MASK: 255.255.255.0

```
        
DEFAULT GATEWAY: 10.1.2.1
```

```
TFTP SERVER: 10.1.1.2
```

TFTP FILE: c1700-y-mz.122-15.t5.bin

Invoke this command for disaster recovery only.

WARNING: all existing data in all partitions on flash will be lost!

Do you wish to continue? y/n: [n]: y

Receiving c1700-y-mz.122-15.t5.bin from 10.1.1.2

[illegible]


```
ignore system config info
console baud: 115200
boot: image specified by the boot system commands
      or default to: cisco2-C1700

do you wish to change the configuration? y/n [n]: n

You must reset or power cycle for new config to take effect
rommon 2 > reset

System Bootstrap, Version 12.2(7r)XM2, RELEASE SOFTWARE (fc1)
TAC Support: http://www.cisco.com/tac
Copyright (c) 2003 by cisco Systems, Inc.
PC = 0xffff0c93c, Vector = 0x500, SP = 0xff002780
C1700 platform with 32768 Kbytes of main memory

PC = 0xffff0c93c, Vector = 0x500, SP = 0x8000486c

monitor: command "boot" aborted due to user interrupt
rommon 1 > xmodem c1700-y-mz.122-15.t5.bin
Do not start the sending program yet...
      File size      Checksum    File name
BB0
*** line too large ***

Do you wish to continue? y/n [n]: n

Do you wish to continue? y/n [n]: y
Ready to receive file c1700-y-mz.122-15.t5.bin ...

--
Uruchamianie serwera www do konfiguracji rutera przez http
--

Router(config)#ip http server
```

From:
<https://kamil.orchia.pl/> - **kamil.orchia.pl**

Permanent link:
<https://kamil.orchia.pl/doku.php?id=cisco-instos&rev=1364303396>

Last update: **2018/07/16 11:47**

